

gracedigital



REMOTE CONTROL CODES for GDI-IRC6000, GDI-IRC7500, GDI-IRC700

HEADER

```
name  lircd_config592.conf
bits      16
flags    SPACE_ENC|CONST_LENGTH
eps      30
aeps     100
header   9020  4463
one      594   1652
zero     594   530
ptrail   592
repeat   9027  2220
pre_data_bits  16
pre_data      0xFF
gap           107890
toggle_bit    0
```

STANDARD CODES

POWER	0x40BF
DYNAMIC_1	0x609F
DYNAMIC_2	0x50AF
DYNAMIC_3	0x708F
SKIP_PREVIOUS	0xC03F
STOP	0x0AF5
PLAY_PAUSE	0xD02F
SKIP_NEXT	0xF00F
MENU_TOP	0x8A75
RC_UP	0xE01F
VOL_UP	0xCA35
BACK	0x02FD
SELECT	0x12ED
MUTE	0x32CD
ALARM	0x22DD
RC_DOWN	0x807F
VOL_DOWN	0xB04F
PRESET_1	0x827D

PRESET_2	0xA05F
PRESET_3	0x906F
PRESET_4	0xA25D
PRESET_5	0x926D
PRESET_6	0xB24D
PRESET_7	0x42BD
PRESET_8	0x629D
PRESET_9	0x728D
PRESET_10	0xE21D
BROWSE_QUEUE	0xC23D
REPLY	0x52AD